



ACR1 CRT



This valve measures 490x135mm overall and has a 6 clip base and 5 side connectors

Heater voltage	4V
Heater current	1.1A
Max final anode voltage	4kV
X plate sensitivity	675/Va3 mm/V
Y plate sensitivity	600/Va3 mm/V
Typical operating conditions	
Final anode voltage	3kV
Second anode voltage	600V
Beam current	15µA

Looking from the base end with the single clip facing downwards, the connections from left to right on the 5 sequential clips are Cathode, Grid, Heater, Heater and Anode 2. At this angle, the side connection to the left is Y2, to the top is X2, to the right is Y1 and the two facing downwards are X1 and Anode 3. The single clip is Anode 1.







This file was last modified 10:34:04, Tuesday June 09, 2015